


# Technical Specification

**Product Code:** CSK003

**Description:** Outdoor Smart Socket Outlet & Hub Kit



## General Information

<b>Dimensions (mm)</b>	146 (W) x 86 (H) x 9.5 (D)	
<b>Plate Fixing Centres - Horizontal (mm)</b>	120.6	
<b>Style</b>	Rounded Profile	
<b>Finish</b>	Polar White	
<b>Materials</b>	Front Plate: Urea Terminals: Brass Internal Busbars: Formed Pressed Brass	Rear Housing: Nylon Terminal Screws: Steel & Yellow Passivated Electronics: PCB & Electronic Components
<b>Rated Voltage (V~) (Ue)</b>	250	<b>Frequency (Hz)</b> 50
<b>Resistive Load Rating (A)</b>	13	
<b>Termination Type</b>	Screw	
<b>Terminal Size (mm)</b>	5.7 x 4.8	<b>Terminal Torque Value (Nm)</b> 1.2
<b>Terminal Capacity - Solid (mm²)</b>	3 x 2.5 or 2 x 4	
<b>Single Pole Switched</b>	Yes	<b>Signal Transmission Frequency</b> 2.4GHz
<b>3 Pin Safety Shuttered</b>	Yes	
<b>Twin Earth Terminals</b>	Yes	
<b>Protocol</b>	Zigbee	
<b>Open Air Wireless Range (M)</b>	<160	
<b>Standby Current (mA)</b>	1	
<b>Indicator Colour</b>	White & Orange	
<b>Minimum Back Box Depth (mm)</b>	25	
<b>Ingress Protection</b>	IP20	
<b>Operational Temperature (°C)</b>	-5 to +40	
<b>Standards</b>	BS 1363-2 BS EN 61000-6-1 BS EN 61000-6-3 BS EN 60669-2-1 in conjunction with BS EN 60669-1	

**Additional Information** 3 pin safety shutter. The shutter will only open once all three plug pins are inserted.  
Zigbee signal mesh  
Each outlet enables manual control (unless locked), wireless control and automated control  
Voice control via ClickSmart+ Hub using Alexa and/or Google Home  
Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.  
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.  
Accepts standard two gang accessory plates.

**Kit Components Supplied** 1 x Smart Socket Outlets  
1 x 2 Gang Weatherproof Enclosure  
1 x Gateway Hub  
Socket Plate Fixing Screws, Socket Screw Caps, Instruction Manual

**Programming Information** With hub and app setup and socket wired and powered, press one of the switches for five to ten seconds, the orange LED indicator starts flashing. Can be paired with hub via app.

**Product Code:** CSK003

**Description:** Outdoor Smart Socket Outlet & Hub Kit



**General Information**

<b>Dimensions (mm)</b>	158 (W) x 158 (H) x 90 (D)		
<b>Finish</b>	Anthracite Grey		
<b>Gasket Colour</b>	Black		
<b>Materials</b>	Cover, Housing & Clip: Polycarbonate	Seal & Gasket: Rubber	
<b>Maximum Accessory Depth (mm)</b>	35		
<b>Back Box Knockouts - Total (mm)</b>	8 x Ø20		
<b>Back Box Knockouts - Top (mm)</b>	1 x Ø20		
<b>Back Box Knockouts - Bottom (mm)</b>	2 x Ø20		
<b>Ingress Protection</b>	IP66		
<b>Operational Temperature (°C)</b>	-5 to +40		

**Standards** BS 5733, BS EN 60529



**General Information**

<b>Dimensions (mm)</b>	90 (L) x 90 (W) x 23 (D)		
<b>Finish</b>	White		
<b>Materials</b>	Housing: Polycarbonate	Electronics: PCB & Electronic Components	
<b>Rated Voltage (DC)</b>	1.8 - 3.3		
<b>Protocol</b>	Zigbee	<b>Signal Transmission Frequency</b>	400MHz
<b>Wireless Technology</b>	WIFI 801.11 b/g/n		
<b>System Requirements</b>	Mobile Device Running IOS 8 or Higher or Android 4.1x or Higher.		
<b>Indicator Colour</b>	Green		
<b>Ingress Protection</b>	IP20		
<b>Working Humidity</b>	10%-90%RH (Non-condensing)		
<b>Operational Temperature (°C)</b>	-10 to +55		

**Standards** BS EN 60950-1, BS EN 55035, BS EN 61000-3-2, BS EN 61000-3-3, BS EN 62311

**Additional Information**

Required for controlling Zigbee devices via the app and voice control  
 Overview of how many devices can be connected:  
 • Hardwired Connected Devices Only: 256  
 • Battery Powered Devices Only (With x1 Hub): 32  
 • Mix of Both Battery Powered and Hardwired: 256 with a Maximum of 62 Battery Powered Devices  
 NOTE: If you are pairing more than 128 devices within the range, please contact technical support on +44 (0) 1827 63454

**Warranty** 5 Years

**Hub Components Supplied** Smart Hub, UK Plug-in Power Adaptor, Ethernet Cable

**Programming Information** Once paired to the app all Zigbee devices and voice control can be added.